



E-Star Power Development Co., Ltd. (E-STAR)
 1F., No.40, Juren Ln., Sec. 2, Sanmin Rd., Banciao Dist., New Taipei City
 22069, Taiwan (R.O.C.)
 Phone : 886-2-2957 5580 Fax : 886-2-2957 7473

40W/60W/100W DIN RAIL power supply > CFM40C/60C/101C



Features

- * Universal Input Range 90~264VAC
- * Efficiency up to 90%
- * Meets EN55022 and CISPR/FCC Class B
- * Continuous Short Circuit Protection
- * LED Indicator for Power ON
- * Can be Installed on DIN rail TS-35/7.5 or 15



CFM40CXXX-DR Series

MODEL	OUTPUT VOLTAGE	OUTPUT CURRENT	RIPPLE & NOISE	VOLTAGE ACCURACY	LINE REGULATION	LOAD REGULATION	% EFF. (Typ.)
CFM40C033-DR	3.3 V	6 A	50mV	±1%	±0.5%	±1%	70%
CFM40C050-DR	5 V	6 A	1%	±1%	±0.5%	±1%	76%
CFM40C090-DR	9 V	4.45 A	1%	±1%	±0.5%	±1%	84%
CFM40C120-DR	12 V	3.34 A	1%	±1%	±0.5%	±1%	85%
CFM40C150-DR	15 V	2.67 A	1%	±1%	±0.5%	±1%	85%
CFM40C240-DR	24 V	1.67 A	1%	±1%	±0.5%	±1%	85%
CFM40C300-DR	30 V	1.33 A	1%	±1%	±0.5%	±1%	86%
CFM40C360-DR	36 V	1.11 A	1%	±1%	±0.5%	±1%	87%
CFM40C480-DR	48 V	0.834 A	1%	±1%	±0.5%	±1%	87%

CFM60CXXX-DR Series

MODEL	OUTPUT VOLTAGE	OUTPUT CURRENT	RIPPLE & NOISE	VOLTAGE ACCURACY	LINE REGULATION	LOAD REGULATION	% EFF. (Typ.)
CFM60C033-DR	3.3 V	8 A	50mV	±1%	±0.5%	±1%	72%
CFM60C050-DR	5 V	8 A	1%	±1%	±0.5%	±1%	77%
CFM60C090-DR	9 V	6.67 A	1%	±1%	±0.5%	±1%	84%
CFM60C120-DR	12 V	5 A	1%	±1%	±0.5%	±1%	85%
CFM60C150-DR	15 V	4 A	1%	±1%	±0.5%	±1%	86%
CFM60C240-DR	24 V	2.5 A	1%	±1%	±0.5%	±1%	86%
CFM60C300-DR	30 V	2 A	1%	±1%	±0.5%	±1%	86%
CFM60C360-DR	36 V	1.67 A	1%	±1%	±0.5%	±1%	88%
CFM60C480-DR	48 V	1.25 A	1%	±1%	±0.5%	±1%	88%

CFM101CXXX-DR Series

MODEL	OUTPUT VOLTAGE	OUTPUT CURRENT	RIPPLE & NOISE	VOLTAGE ACCURACY	LINE REGULATION	LOAD REGULATION	% EFF. (Typ.)	PF (Typ.)
CFM101C120-DR	12 V	8.4 A	1%	±1%	±0.5%	±1%	87%	0.9
CFM101C150-DR	15 V	6.7 A	1%	±1%	±0.5%	±1%	87%	0.9
CFM101C200-DR	20 V	5 A	1%	±1%	±0.5%	±1%	88%	0.9
CFM101C240-DR	24 V	4.2 A	1%	±1%	±0.5%	±1%	88%	0.9
CFM101C480-DR	48 V	2.1 A	1%	±1%	±0.5%	±1%	90%	0.9

