



E-Star Power Development Co., Ltd. (E-STAR)

No.305, Sec. 2, Jhongshan Rd., Banciao City, Taipei County 22067, Taiwan

Phone : 886-2-2957 5580 Fax : 886-2-2957 7473

**8W Travel output power supply < PA1008-IB**

**Features:**

Over-Voltage Protection  
 Over-Current Protection  
 Limit current Protection(Optional)  
 Short-circuit Protection  
 Hi-pot & 100% ATE(Chroma)Tested  
 100%Burn-in under High  
 Ambient Temperature(45℃)  
 Low Ripple/Noise  
 MTBF Above 50000 HRS At 25℃  
 LVD authentication  
 Limited Power Sources(LPS)  
 CEC IV Efficiency  
 Regulations Compliance  
 Cispr 22 CLASS B,VCCI CLASS B,  
 FCC Part15 CLASS B, Compliance



**Model No.**

**PA1080-IB**

**AC input voltage range**

100~240VAC / 50~60Hz

**AC inrush current (max.)**

40A Max.

**Over Load Protection**

Auto Recovery

**Short Protection**

Auto Recovery

**Withstand voltage**

I/P - O/P: 3K Vac

**Working temperature**

0~40℃ full load , de-rating : 41~50 ℃ 3% / ℃.

**Storage Temperature**

-20℃ ~ +85℃

**Operating Relative Humidity**

5% to 90% non-condensing

**No Load Standby Power**

No load power consumption less than 0.5 W

**Safety standards**

CB,UL,CUL,GS,PSE,C-TICK,CEC

**EMC standards**

CE,FCC,BSMI

ModelNo.	PA1008-1IB		PA1008-2IB			PA1008-3IB	
P/No.	PA1008-030IB~PA1008-070IB		PA1008-071SIB~PA1008-150IB			PA1008-151SIB~PA1008-300IB	
Output V	3V~4.8V	4.9V~7.0V	7.1V~8.9V	9.0V~10.5V	10.6V~15.0V	15.1V~21.0V	21.1V~30.0V
Output Current	1.5A	1.5A	1.14A	1.0A	0.85A	0.6A	0.43A
Output Watt	7.5W	8W	8W	9.3W	9.3W	9.3W	9.3W



E-Star Power Development Co., Ltd. (E-STAR)  
No.305, Sec. 2, Jhongshan Rd., Banciao City, Taipei County 22067, Taiwan  
Phone : 886-2-2957 5580 Fax : 886-2-2957 7473

**8W Travel output power supply < PA1008-IB**

