



E-Star Power Development Co., Ltd. (E-STAR)  
 1F, No.40, Juren Ln., Sec. 2, Sanmin Rd., Banciao Dist., New Taipei City  
 22069, Taiwan (R.O.C.)  
 Phone : 886-2-2957 5580 Fax : 886-2-2957 7473

**28 ~ 30W Travel Power Supply < PA1024/PS1024**

## Features

Over-Voltage Protection  
 Over-Current Protection

Short-circuit Protection  
 100%Hi-pot & ATE Tested

100%Burn-in under (45°C)

Low Ripple/Noise  
 MTBF 50000 HRS At 25°C

LVD authentication  
 Limited Power Sources(LPS)

DoE VI and CoC Tier 2 VI Efficiency  
 Regulations Compliance

Cispr 22 CLASS B, VCCI CLASS B,  
 FCC Part15 CLASS B, Compliance

## PA1024/PS1024 Series Wall Mount-Interchangeable Plug In



## Specification

Model No		PA1024-xxxxxyyzzz / PS1024-xxxxxyyzzz			
Transformer		EE25-1	EE25-2	EE25-3	EE25-4
Item					
Output Voltage		3~7.0V	7.1~15.0V	15.1~30.0V	30.1~57.0V
Output Current(Max.)		4A	4A	1.98A	0.99A
Output Power(Max.)		28W	30W	30W	30W
Input Voltage		AC90~264V			
Input Frequency		47~63Hz			
Input Current		0.6A Max			
Inrush Current		40A Max			
Line Regulation		1% Max			
Ripple&Noise		1% Max			
Load Regulation		5% Max			
Efficiency		DoE VI & CoC Teir 2 VI			
Operating Temperature		0~40°C			
Storage Temperature		-20~85°C			
Over-Voltage Protection		Auto Recovery			
Short-circuit Protection		Auto Recovery			
Safety Standard		CB,CCC,UL,CUL,TUV-GS,LVD,PSE,NOM,SAA,RCM,MEPS,DoE			
EMC(EMI/EMS)		CE,FCC,VCCI,RCM			



E-Star Power Development Co., Ltd. (E-STAR)  
 1F., No.40, Juren Ln., Sec. 2, Sanmin Rd., Banciao Dist., New Taipei City  
 22069, Taiwan (R.O.C.)  
 Phone : 886-2-2957 5580 Fax : 886-2-2957 7473

**28 ~ 30W Travel Power Supply < PA1024/PS1024**

機種編碼 Products code:

